














GE UNIK 5000 | PRESSURE SENSOR

SENSOR WIRING TABLE

Sensor Model	Sensor Pin	Kintech Cable Colors		Orbit 360			EOL Zenith	
				Section	Terminal	Type	Section	Terminal
 Output: 0-5V 600-1100mbar	Pin 2		Brown	Analog Channels		(-)	Analog Inputs	
	Pin 3		White	Analog Channels		Signal	Analog Inputs Extra Analog	
	Pin 1		Green	Analog Channels		*Output	**OUT	
	Pin E		Yellow Green	Power Input			BAT	

Note: *Output: Pulsating Bat+ with current limited (2A). Only 1 sensor must be powered.

**OUT: Pulsating Bat+ with current limited (2A). Only 1 sensor must be powered.

HOW TO CONFIGURE IN ATLAS

Open Atlas and go to the data logger you are working on. Scroll to the “channels” section and select the following type and model:

- Group: Analog channels
- Sensor Type: Voltage
- Sensor Model: **VOLTS**

Slope: 100

Offset: 600

HOW TO CONFIGURE IN EOL MANAGER

Open EOL Manager and go to the data logger you are working on. Open the “inputs” tab and select the following type and model:

- Group: Analog inputs
- Type: Voltmeter
- Model: **Generic Voltmeter**

Slope: 100

Offset: 600

Last modified: 05.06.2020

For more information please contact support@kintech-engineering.com or visit our website www.kintech-engineering.com

